## **USAT**

## **INVERTER 800W**

Model:SDA-800



## **Features:**

Modified Sine Wave Power Inverter Regulated output to protect equipment from voltage spikes and fluctuations

Low voltage shutdown prevents total battery discharge DC terminals for direct battery connection totally silent operation

Compact size for convenient use and storage

LED indicator confirms fault condition

Power ON/OFF Switch

## **Specification:**

1. Input voltage Range: DC10-15V/20-30V

2. Output voltage: AC220V

Output frequency: 50Hz+/-2Hz
 Fuse: 10A/15A/20A/40A/70A

5. Low battery alarm (nominal): 10.4-11.0v

6. Low battery shutdown point (nominal): 9.7-10.3v7. High battery shutdown point (nominal): 14.5-15.5v

8. Battery drain with on AC (at 12V input): <0.3A

9. Peak efficiency: >90%

10. Durative output power: 800W11. Twinkling maximum power: 1600W

12. Output waveform: Modified Modified Sine

13. Size: 191\*95\*55(mm)

14. Weight: 821g